



About Product

In gasoline and diesel portable generators, the GO-BUSINESS GO-MOTOR generator set offers high performance and reliability. For all manufactured generator sets, prior product testing and factory manufacturing testing are carried out.

POWER

VOLTAGE	Standby Power (ESP)		Prime Power (PRP)		Amper	PWR (HP)
	kVA	kW	kVA	kW	A	hp
220	3,88	3,10	3,50	2,80	12,5	7,00

General Features

Model Name	GO-BJ4000
Fuel Type Used	PETROL
Engine	GO170F
Engine Cylinder/Model	1 cylinders - in line
Alternator Brand	BUSINESS
Phase	220 MONOPHASE

Engine Specifications

Oil Capacity (Including Filter) (lt)	0.6 L
Fuel Tank Capacity	15 L
Speed (r/min)	3000/6000
Cooling Method	AIR COOLED
Battery and Capacity (Quantity/V)	1x12
System	String
Battery Charging	12 V

Size And Weight

Width (mm)	605
Length (mm)	470
Height (mm)	435
Weight (kg)	45